



SILICON TRANSISTOR μ PA811T

HIGH-FREQUENCY LOW NOISE AMPLIFIER NPN SILICON EPITAXIAL TRANSISTOR (WITH BUILT-IN 2 \times 2SC4228) SMALL MINI MOLD

The μ PA811T has built-in 2 low-voltage transistors which are designed to amplify low noise in the VHF band to the UHF band.

FEATURES

- Low Noise
NF = 1.9 dB TYP. @ f = 2 GHz, $V_{CE} = 1$ V, $I_c = 3$ mA
- High Gain
 $|S_{21e}|^2 = 6.5$ dB TYP. @ f = 2 GHz, $V_{CE} = 1$ V, $I_c = 3$ mA
- A Small Mini Mold Package Adopted
- Built-in 2 Transistors (2 \times 2SC4228)

ORDERING INFORMATION

PART NUMBER	QUANTITY	PACKING STYLE
μ PA811T	Loose products (50 PCS)	Embossed tape 8 mm wide. Pin 6 (Q1 Base), Pin 5 (Q1 Emitter), Pin 4 (Q2 Emitter) face to perforation side of the tape.
μ PA811T-T1	Taping products (3 KPCS/Reel)	

Remark To order evaluation samples, please contact your nearby sales office.
Part number for sample order: μ PA811T-A (Unit sample quantity is 50 pcs.)



ABSOLUTE MAXIMUM RATINGS ($T_A = 25$ °C)

PARAMETER	SYMBOL	RATING	UNIT
Collector to Base Voltage	V_{CBO}	20	V
Collector to Emitter Voltage	V_{CEO}	10	V
Emitter to Base Voltage	V_{EBO}	1.5	V
Collector Current	I_c	35	mA
Total Power Dissipation	P_T	150 in 1 element 200 in 2 elements ^{Note}	mW
Junction Temperature	T_j	150	°C
Storage Temperature	T_{stg}	-65 to +150	°C


Note 110 mW must not be exceeded in 1 element.

PACKAGE DRAWINGS

(Unit: mm)



PIN CONFIGURATION (Top View)



PIN CONNECTIONS

- | | |
|-------------------|-----------------|
| 1. Collector (Q1) | 4. Emitter (Q2) |
| 2. Base (Q2) | 5. Emitter (Q1) |
| 3. Collector (Q2) | 6. Base (Q1) |

The information in this document is subject to change without notice.

ELECTRICAL CHARACTERISTICS (T_A = 25 °C)





PARAMETER	SYMBOL	CONDITION	MIN.	TYP.	MAX.	UNIT
Collector Cutoff Current	I _{CBO}	V _{CB} = 10 V, I _E = 0			1.0	μA
Emitter Cutoff Current	I _{EBO}	V _{EB} = 1 V, I _C = 0			1.0	μA
DC Current Gain	h _{FE}	V _{CE} = 3 V, I _C = 5 mA ^{Note 1}	80		200	
Gain Bandwidth Product	f _T	V _{CE} = 3 V, I _C = 5 mA	5.5	8.0		GHz
Feed-back Capacitance	C _{re}	V _{CB} = 3 V, I _E = 0, f = 1 MHz ^{Note 2}			0.7	pF
Insertion Power Gain	S _{21e} ²	V _{CE} = 3 V, I _C = 5 mA, f = 2 GHz	5.5	7.5		dB
Noise Figure	NF	V _{CE} = 3 V, I _C = 5 mA, f = 2 GHz		1.9	3.2	dB
h _{FE} Ratio	h _{FE1} /h _{FE2}	V _{CE} = 3 V, I _C = 5 mA A smaller value among h _{FE} of h _{FE1} = Q1, Q2 A Larger value among h _{FE} of h _{FE2} = Q1, Q2	0.85			






- Notes**
1. Pulse Measurement: P_w ≤ 350 μs, Duty cycle ≤ 2 %
 2. Measured with 3-pin bridge, emitter and case should be connected to guard pin of bridge.

h_{FE} CLASSIFICATION

Rank	FB	GB
Marking	44R	45R
h _{FE} Value	80 to 160	125 to 250

TYPICAL CHARACTERISTICS (T_A = 25 °C)





S-PARAMETERS

V_{CE} = 3 V, I_c = 1 mA

FREQUENCY MHz	S ₁₁		S ₂₁		S ₁₂		S ₂₂	
	MAG	ANG	MAG	ANG	MAG	ANG	MAG	ANG
100.00	0.969	-7.9	3.625	172.0	0.016	85.0	0.999	-3.6
200.00	0.957	-14.7	3.405	165.9	0.031	80.7	0.989	-6.4
300.00	0.909	-21.2	3.366	156.4	0.046	73.3	0.961	-10.4
400.00	0.909	-27.4	3.218	153.3	0.059	70.9	0.955	-12.4
500.00	0.895	-33.5	3.147	144.8	0.071	66.4	0.913	-14.2
600.00	0.876	-42.4	3.150	141.2	0.083	65.6	0.913	-16.7
700.00	0.821	-49.4	3.040	132.0	0.092	60.7	0.896	-18.0
800.00	0.750	-56.0	2.966	126.2	0.105	58.0	0.888	-21.1
900.00	0.710	-60.5	2.779	119.6	0.110	55.8	0.869	-23.3
1000.00	0.673	-65.3	2.640	114.1	0.119	51.5	0.840	-27.3
1100.00	0.658	-72.2	2.532	110.6	0.124	51.0	0.805	-28.9
1200.00	0.625	-78.4	2.504	105.6	0.129	48.2	0.758	-30.8
1300.00	0.573	-85.4	2.427	102.7	0.138	46.2	0.738	-31.1
1400.00	0.537	-91.2	2.350	96.2	0.137	44.5	0.706	-31.5
1500.00	0.505	-97.1	2.305	92.3	0.143	42.0	0.709	-32.1
1600.00	0.479	-103.2	2.210	88.3	0.142	43.8	0.693	-32.6
1700.00	0.448	-110.2	2.152	83.6	0.148	41.9	0.689	-35.3
1800.00	0.424	-115.4	2.101	81.0	0.155	42.9	0.678	-36.5
1900.00	0.399	-120.9	2.034	75.9	0.157	40.4	0.650	-39.1
2000.00	0.389	-127.2	1.987	71.7	0.165	38.1	0.631	-40.5

V_{CE} = 3 V, I_c = 3 mA

FREQUENCY MHz	S ₁₁		S ₂₁		S ₁₂		S ₂₂	
	MAG	ANG	MAG	ANG	MAG	ANG	MAG	ANG
100.00	0.903	-14.0	8.928	165.7	0.016	89.5	0.985	-6.5
200.00	0.856	-25.6	8.248	154.2	0.028	74.6	0.951	-11.2
300.00	0.763	-36.2	7.535	141.5	0.042	68.0	0.889	-16.4
400.00	0.713	-44.7	6.882	135.1	0.051	65.0	0.851	-18.6
500.00	0.656	-52.3	6.233	125.9	0.058	61.2	0.785	-20.1
600.00	0.602	-62.4	5.854	121.4	0.067	61.4	0.764	-21.7
700.00	0.536	-70.5	5.342	112.1	0.072	58.8	0.733	-21.9
800.00	0.466	-77.7	4.989	106.9	0.080	57.9	0.717	-23.8
900.00	0.412	-82.8	4.471	100.4	0.084	58.0	0.696	-25.0
1000.00	0.374	-87.8	4.123	95.3	0.091	55.7	0.669	-27.6
1100.00	0.346	-93.4	3.871	92.3	0.095	56.9	0.639	-28.3
1200.00	0.315	-100.2	3.667	88.1	0.100	55.9	0.603	-29.2
1300.00	0.285	-106.7	3.575	86.0	0.108	55.8	0.587	-28.7
1400.00	0.263	-112.8	3.367	81.3	0.111	55.6	0.566	-28.3
1500.00	0.245	-119.7	3.214	78.3	0.118	54.5	0.570	-28.2
1600.00	0.230	-126.7	3.038	75.5	0.121	57.3	0.561	-28.3
1700.00	0.214	-135.0	2.918	72.3	0.129	55.9	0.559	-30.5
1800.00	0.202	-141.2	2.821	69.9	0.137	57.2	0.553	-31.5
1900.00	0.192	-147.9	2.696	65.8	0.143	54.8	0.532	-33.7
2000.00	0.193	-154.2	2.613	61.8	0.152	53.2	0.515	-34.7

S-PARAMETERS

V_{CE} = 3 V, I_c = 5 mA

FREQUENCY MHz	S ₁₁		S ₂₁		S ₁₂		S ₂₂	
	MAG	ANG	MAG	ANG	MAG	ANG	MAG	ANG
100.00	0.848	-18.5	12.800	161.3	0.015	78.5	0.974	-8.3
200.00	0.766	-33.1	11.314	146.2	0.026	71.6	0.913	-14.0
300.00	0.647	-45.5	9.862	132.5	0.038	66.4	0.829	-19.0
400.00	0.575	-54.3	8.611	125.0	0.044	64.0	0.778	-20.4
500.00	0.506	-62.0	7.527	116.3	0.052	62.0	0.712	-20.9
600.00	0.450	-71.5	6.847	112.2	0.058	63.0	0.691	-21.5
700.00	0.393	-79.6	6.116	103.6	0.064	61.6	0.666	-21.0
800.00	0.335	-86.5	5.624	99.2	0.072	61.8	0.652	-22.2
900.00	0.290	-91.7	4.970	93.3	0.076	62.4	0.637	-23.1
1000.00	0.260	-97.0	4.521	88.7	0.084	60.4	0.616	-25.3
1100.00	0.236	-102.5	4.202	86.2	0.088	62.0	0.592	-25.7
1200.00	0.213	-109.7	3.947	82.4	0.094	61.2	0.561	-26.4
1300.00	0.193	-116.7	3.792	80.3	0.102	61.3	0.550	-25.7
1400.00	0.178	-123.3	3.468	76.1	0.106	61.1	0.532	-25.1
1500.00	0.168	-131.8	3.408	73.8	0.115	60.2	0.538	-25.1
1600.00	0.161	-139.7	3.218	71.4	0.118	62.3	0.533	-25.2
1700.00	0.153	-149.2	3.085	68.7	0.128	60.8	0.532	-27.5
1800.00	0.148	-156.1	2.980	66.4	0.137	61.9	0.527	-28.5
1900.00	0.143	-163.5	2.840	62.7	0.143	59.4	0.507	-30.7
2000.00	0.149	-169.9	2.752	58.8	0.153	57.6	0.492	-31.8

PHASE

NOTICE

1. Descriptions of circuits, software and other related information in this document are provided only to illustrate the operation of semiconductor products and application examples. You are fully responsible for the incorporation of these circuits, software, and information in the design of your equipment. California Eastern Laboratories and Renesas Electronics assumes no responsibility for any losses incurred by you or third parties arising from the use of these circuits, software, or information.
2. California Eastern Laboratories has used reasonable care in preparing the information included in this document, but California Eastern Laboratories does not warrant that such information is error free. California Eastern Laboratories and Renesas Electronics assumes no liability whatsoever for any damages incurred by you resulting from errors in or omissions from the information included herein.
3. California Eastern Laboratories and Renesas Electronics do not assume any liability for infringement of patents, copyrights, or other intellectual property rights of third parties by or arising from the use of Renesas Electronics products or technical information described in this document. No license, express, implied or otherwise, is granted hereby under any patents, copyrights or other intellectual property rights of California Eastern Laboratories or Renesas Electronics or others.
4. You should not alter, modify, copy, or otherwise misappropriate any Renesas Electronics product, whether in whole or in part. California Eastern Laboratories and Renesas Electronics assume no responsibility for any losses incurred by you or third parties arising from such alteration, modification, copy or otherwise misappropriation of Renesas Electronics product.
5. Renesas Electronics products are classified according to the following two quality grades: "Standard" and "High Quality". The recommended applications for each Renesas Electronics product depends on the product's quality grade, as indicated below. "Standard": Computers; office equipment; communications equipment; test and measurement equipment; audio and visual equipment; home electronic appliances; machine tools; personal electronic equipment; and industrial robots etc. "High Quality": Transportation equipment (automobiles, trains, ships, etc.); traffic control systems; anti-disaster systems; anti-crime systems; and safety equipment etc. Renesas Electronics products are neither intended nor authorized for use in products or systems that may pose a direct threat to human life or bodily injury (artificial life support devices or systems, surgical implantations etc.), or may cause serious property damages (nuclear reactor control systems, military equipment etc.). You must check the quality grade of each Renesas Electronics product before using it in a particular application. You may not use any Renesas Electronics product for any application for which it is not intended. California Eastern Laboratories and Renesas Electronics shall not be in any way liable for any damages or losses incurred by you or third parties arising from the use of any Renesas Electronics product for which the product is not intended by California Eastern Laboratories or Renesas Electronics.
6. You should use the Renesas Electronics products described in this document within the range specified by California Eastern Laboratories, especially with respect to the maximum rating, operating supply voltage range, movement power voltage range, heat radiation characteristics, installation and other product characteristics. California Eastern Laboratories shall have no liability for malfunctions or damages arising out of the use of Renesas Electronics products beyond such specified ranges.
7. Although Renesas Electronics endeavors to improve the quality and reliability of its products, semiconductor products have specific characteristics such as the occurrence of failure at a certain rate and malfunctions under certain use conditions. Further, Renesas Electronics products are not subject to radiation resistance design. Please be sure to implement safety measures to guard them against the possibility of physical injury, and injury or damage caused by fire in the event of the failure of a Renesas Electronics product, such as safety design for hardware and software including but not limited to redundancy, fire control and malfunction prevention, appropriate treatment for aging degradation or any other appropriate measures. Because the evaluation of microcomputer software alone is very difficult, please evaluate the safety of the final products or systems manufactured by you.
8. Please contact a California Eastern Laboratories sales office for details as to environmental matters such as the environmental compatibility of each Renesas Electronics product. Please use Renesas Electronics products in compliance with all applicable laws and regulations that regulate the inclusion or use of controlled substances, including without limitation, the EU RoHS Directive. California Eastern Laboratories and Renesas Electronics assume no liability for damages or losses occurring as a result of your noncompliance with applicable laws and regulations.
9. Renesas Electronics products and technology may not be used for or incorporated into any products or systems whose manufacture, use, or sale is prohibited under any applicable domestic or foreign laws or regulations. You should not use Renesas Electronics products or technology described in this document for any purpose relating to military applications or use by the military, including but not limited to the development of weapons of mass destruction. When exporting the Renesas Electronics products or technology described in this document, you should comply with the applicable export control laws and regulations and follow the procedures required by such laws and regulations.
10. It is the responsibility of the buyer or distributor of California Eastern Laboratories, who distributes, disposes of, or otherwise places the Renesas Electronics product with a third party, to notify such third party in advance of the contents and conditions set forth in this document, California Eastern Laboratories and Renesas Electronics assume no responsibility for any losses incurred by you or third parties as a result of unauthorized use of Renesas Electronics products.
11. This document may not be reproduced or duplicated in any form, in whole or in part, without prior written consent of California Eastern Laboratories.
12. Please contact a California Eastern Laboratories sales office if you have any questions regarding the information contained in this document or Renesas Electronics products, or if you have any other inquiries.

NOTE 1: "Renesas Electronics" as used in this document means Renesas Electronics Corporation and also includes its majority-owned subsidiaries.

NOTE 2: "Renesas Electronics product(s)" means any product developed or manufactured by or for Renesas Electronics.

NOTE 3: Products and product information are subject to change without notice.

CEL Headquarters • 4590 Patrick Henry Drive, Santa Clara, CA 95054 • Phone (408) 919-2500 • www.cel.com

For a complete list of sales offices, representatives and distributors,
Please visit our website: www.cel.com/contactus